

Section 2

Formula sheet

This formula sheet will be provided to candidates in the examination and may be used to answer any question.

$$R_T = R_1 + R_2 + R_3$$

$$V_{out} = V_{in} \frac{R_2}{R_1 + R_2}$$

$$\frac{1}{C_T} = \frac{1}{C_1} + \frac{1}{C_2} + \frac{1}{C_3}$$

$$L_T = L_1 + L_2 + L_3$$

$$Z = \sqrt{R^2 + X^2}$$

$$f = \frac{1}{2\pi\sqrt{LC}}$$

$$Q = \frac{2\pi fL}{R} \quad \text{or} \quad \frac{1}{2\pi fCR}$$

$$Q = 2\pi fCR_D$$

$$V_S = V_P \frac{N_s}{N_p}$$

$$I_C = \beta I_B$$

$$c = 3 \times 10^8 \text{ m/s}$$

$$v = f\lambda$$

$$E = \frac{7\sqrt{\text{erp}}}{d}$$

$$\text{erp} = \text{power} \times \text{gain (linear)}$$

$$\frac{1}{R_T} = \frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_3}$$

$$P = VI = \frac{V^2}{R} = I^2R$$

$$C_T = C_1 + C_2 + C_3$$

$$\frac{1}{L_T} = \frac{1}{L_1} + \frac{1}{L_2}$$

$$V_T = \sqrt{V_R^2 + V_C^2} \quad (\text{or } V_L^2)$$

$$T = \frac{1}{f}$$

$$Q = \frac{f_c}{f_U - f_L} = \frac{\text{centre frequency}}{\text{bandwidth}}$$

$$I_P = I_S \frac{N_s}{N_p}$$

$$f_{\text{step}} = \frac{f_{\text{crystal}}}{A}$$

$$\text{Gain (loss)} = 10 \log_{10} \frac{\text{power out}}{\text{power in}} \text{ dB}$$

$$\text{Gain (loss)} = 20 \log_{10} \frac{\text{voltage out}}{\text{voltage in}} \text{ dB}$$

$$\text{Return Loss} = 10 \log_{10} \frac{\text{Reflected power}}{\text{Incident power}} \text{ dB}$$

$$\text{Gain} = 10 \log_{10} \frac{\text{power from Yagi}}{\text{power from dipole}} \text{ dBd}$$

$$V = IR$$

$$V_{\text{rms}} = \frac{V_{\text{peak}}}{\sqrt{2}}$$

$$C = \frac{kA}{d} \quad \text{where } k = \epsilon_0 \epsilon_r$$

$$X_L = 2\pi fL$$

$$X_C = \frac{1}{2\pi fC}$$

$$\tau = CR$$

$$R_D = \frac{L}{CR}$$

$$Z_P = Z_S \left(\frac{N_p}{N_s} \right)^2$$

$$F_{\text{out}} = f_{\text{crystal}} \frac{N}{A}$$

$$\text{SWR} = \frac{V_{\text{max}}}{V_{\text{min}}} = \frac{V_f + V_r}{V_f - V_r}$$

$$Z_0^2 = Z_{\text{in}} \times Z_{\text{out}}$$

$$bw = 2(AF_{\text{max}} + \Delta f)$$